

04/28/00
jc713 U.S. PTO

S&H Form: PTO/SB/05 (12/97)

UTILITY PATENT APPLICATION TRANSMITTAL (Only for new nonprovisional applications under 37 CFR 1.53(b))	Attorney Docket No. 837.1953/JDH
	First Named Inventor or Application Identifier: Shigeki WATANABE
	Express Mail Label No.

APPLICATION ELEMENTS See MPEP chapter 600 concerning utility patent application contents.	ADDRESS TO: Assistant Commissioner for Patents Box Patent Application Washington, DC 20231
---	---

1. ☒ Fee Transmittal Form
2. ☒ Specification, Claims & Abstract [Total Pages: 31]
3. ☒ Drawing(s) (35 USC 113) [Total Sheets: 6]
4. ☒ Oath or Declaration [Total Pages: 3]
 - a. ☒ Newly executed (original or copy)
 - b. ☐ Copy from a prior application (37 CFR 1.63(d)) (for continuation/divisional with Box 17 completed)
 - i. ☐ **DELETION OF INVENTOR(S)**
Signed statement attached deleting inventor(s) named in the prior application, see 37 CFR 1.63(d)(2) and 1.33(b).
5. ☐ Incorporation by Reference (usable if Box 4b is checked)
The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under Box 4b, is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.
6. ☐ Microfiche Computer Program (Appendix)
7. ☐ Nucleotide and/or Amino Acid Sequence Submission (if applicable, all necessary)
 - a. ☐ Computer Readable Copy
 - b. ☐ Paper Copy (identical to computer copy)
 - c. ☐ Statement verifying identity of above copies

jc678 U.S. PTO
09/560723
04/28/00

ACCOMPANYING APPLICATION PARTS

8. ☒ Assignment Papers (cover sheet & document(s))
9. ☐ 37 CFR 3.73(b) Statement (when there is an assignee) [] Power of Attorney
10. ☐ English Translation Document (if applicable)
11. ☒ Information Disclosure Statement (IDS)/PTO-1449[X] Copies of IDS Citations
12. ☒ Preliminary Amendment
13. ☒ Return Receipt Postcard (MPEP 503) (Should be specifically itemized)
14. ☐ Small Entity Statement(s) [] Statement filed in prior application, status still proper and desired.
15. ☒ Certified Copy of Priority Document(s) (if foreign priority is claimed)
16. ☐ Other:

17. If a CONTINUING APPLICATION, check appropriate box and supply the requisite information:

[] Continuation [] Divisional [] Continuation-in-part (CIP) of prior application No: /

18. CORRESPONDENCE ADDRESS

STAAS & HALSEY LLP
Attn: James D. Halsey, Jr.
700 Eleventh Street, N.W., Suite 500
Washington, DC 20001

Telephone: (202) 434-1500
Facsimile: (202) 434-1501

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of:

Shigeki WATANABE

Serial No.: To Be Assigned

Group Art Unit: To Be Assigned

Filed: April 28, 2000

Examiner: To Be Assigned

For: METHOD, DEVICE, AND SYSTEM FOR REGENERATION AND APPLICATION OF
OPTICAL CLOCK

PRELIMINARY AMENDMENT

Assistant Commissioner of Patents and Trademarks
Washington, D.C. 20231

Sir:

Before examination of the above-identified application, please amend the application as follows:

IN THE CLAIMS:

Please AMEND the claims as follows:

Claim 8, line 1, change "claim 6 or 7" to --claim 14--.

REMARKS

This Preliminary Amendment is submitted to improve the form of the claims as originally filed.

It is respectfully requested that this Preliminary Amendment be entered in the above-references application.

Preliminary Amendment


Docket No.: 837.1953/JDH

If any fees are required in connection with the filing of this Preliminary Amendment, please charge same to our Deposit Account No. 19-3935.

Respectfully submitted,

STAAS & HALSEY, LLP

By:



James D. Halsey, Jr.
Registration No.: 22,729

700 Eleventh Street, N.W.
Washington, D.C. 20001
(202) 434-1500

Date: April 28, 2000

**METHOD, DEVICE, AND SYSTEM FOR REGENERATION AND
APPLICATION OF OPTICAL CLOCK**

BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates to a method, device, and system for regeneration and application of an optical clock.

Description of the Related Art

This application is related to U.S. application numbers 09/217,018, 09/386,847 and 09/456,821, which are incorporated herein by reference.

A mode-locked laser (MLL) is one of the most general high-quality laser light sources, and it is broadly classified into an active mode-locked laser and a passive mode-locked laser. The active mode-locked laser is of a type such that amplitude modulation (AM) or frequency modulation (FM) is added under laser oscillation conditions to thereby oscillate pulse light synchronous with the modulation. On the other hand, the passive mode-locked laser is of a type such that such modulation is not added, but external pulse light is input to generate pulse light having a shorter pulse duration in response to the external input pulse light.

Each type of mode-locked laser is most generally used as a short-pulse light source.

The present invention provides an active mode-locked laser in which external signal light (general signal light used in optical communication) is added to oscillate continuous pulse light synchronous with a fundamental frequency (modulation frequency) of the signal light. The continuous pulse light is output as an optical clock. Thus, the active mode-locked laser according to the present invention can be used not only as a high-quality pulse light source, but also as an optical clock regenerator in an optical repeater.

Conventionally known is a device for regenerating an optical clock so configured that input signal light is once converted into an electrical signal by a photodetector such as a photodiode, that a fundamental frequency is electrically extracted according to the converted electrical signal, and that laser light is intensity-modulated at this fundamental frequency to thereby obtain the optical clock. This kind of device is applied to a regenerative repeater in optical fiber communication, for example. However, the operating speed of this device is limited by an electrical circuit related to signal processing, so that the bit rate of

applicable input signal light is limited by the electrical circuit.

Further, another optical clock regenerator employing an active mode-locked laser with an optical modulator (LN (lithium niobate) modulator, EA (electroabsorption) modulator, etc.) inserted therein is also known. In this optical clock regenerator, the optical modulator is modulated at a fundamental frequency electrically regenerated as similarly to the above to regenerate clock pulses.

In any prior art technique mentioned above, it is necessary to perform opto/electric conversion such that signal light is converted into an electrical signal to regenerate an optical clock, and the operation of the device is dependent on the bit rate, pulse shape, etc. of signal light.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention to provide a method, device, and system for regeneration and application of an optical clock not depending on the bit rate, pulse shape, etc. of signal light without the need for opto/electric conversion.

In accordance with a first aspect of the present

invention, there is provided an optical device comprising an optical path provided between an input port and an output port, and an optical loop optically coupled to the optical path. Signal light modulated at a frequency f_s is supplied to the input port. The optical loop comprises an optical amplifier for compensating for a loss in the optical loop so that laser oscillation occurs in the optical loop, an adjuster for adjusting the optical path length of the optical loop so that the frequency f_s becomes equal to an integral multiple of the reciprocal of a recirculation period of the optical loop, and a nonlinear optical medium for mode-locking the laser oscillation in the optical loop according to the signal light.

For example, the nonlinear optical medium comprises a third-order nonlinear optical medium. In this case, amplitude modulation, for example, is performed in the nonlinear optical medium by four-wave mixing using the signal light as pump light, thereby mode-locking the laser oscillation in the optical loop. As a result, an optical clock is regenerated at a frequency equal to the modulation frequency f_s of the signal light.

According to the first aspect of the present invention, the optical clock can be regenerated without

the need for opto/electric conversion and the dependence on the bit rate, pulse shape, etc. of the signal light.

In accordance with a second aspect of the present invention, the optical device further comprises a waveform shaper optically connected to the output port for performing waveform shaping of the signal light according to an optical clock output from the output port. The waveform shaper may be provided by a nonlinear optical loop mirror, for example.

According to the second aspect of the present invention, the waveform shaping can be easily performed according to the optical clock regenerated without the need for opto/electric conversion.

In accordance with a third aspect of the present invention, there is provided a system comprising an optical fiber transmission line for transmitting signal light and an optical device connected to an output end of the optical fiber transmission line. The optical device in this system may be provided by the optical device according to the first or second aspect of the present invention.

In accordance with a fourth aspect of the present invention, there is provided a system comprising an optical fiber transmission line for transmitting signal

light and at least one optical repeater arranged along the optical fiber transmission line. Each of the at least one optical repeater comprises an optical clock regenerator for regenerating an optical clock by mode locking of laser oscillation according to the signal light, and a waveform shaper for performing waveform shaping of the signal light according to the optical clock regenerated by the optical clock regenerator.

In accordance with a fifth aspect of the present invention, there is provided a method comprising the steps of (a) generating laser oscillation in an optical loop including a nonlinear optical medium; (b) introducing signal light modulated at a frequency f_s into said optical loop; (c) adjusting the optical path length of said optical loop so that said frequency f_s becomes equal to an integral multiple of the reciprocal of a recirculation period of said optical loop; and (d) regenerating an optical clock by mode-locking said laser oscillation according to said signal light.

The above and other objects, features and advantages of the present invention and the manner of realizing them will become more apparent, and the invention itself will best be understood from a study of the following description and appended claims with

reference to the attached drawings showing some preferred embodiments of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a first preferred embodiment of the optical device according to the present invention;

FIG. 2 is a block diagram showing a second preferred embodiment of the optical device according to the present invention;

FIG. 3 is a block diagram showing a third preferred embodiment of the optical device according to the present invention;

FIG. 4 is a block diagram showing a fourth preferred embodiment of the optical device according to the present invention;

FIG. 5 is a block diagram showing a preferred embodiment of the system according to the present invention;

FIG. 6 is a block diagram showing a preferred embodiment of each optical repeater shown in FIG. 5; and

FIG. 7 is a block diagram showing a specific embodiment of the optical repeater shown in FIG. 6.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Some preferred embodiments of the present invention will now be described in detail with reference to the attached drawings.

FIG. 1 is a block diagram showing a first preferred embodiment of the optical device according to the present invention. This optical device includes an optical path 6 provided between an input port 2 and an output port 4, and an optical loop 8 optically coupled to the optical path 6. Each of the optical path 6 and the optical loop 8 is provided by an optical fiber, for example. In this case, the optical coupling between the optical path 6 and the optical loop 8 may be made by a fiber fusion type optical coupler 10. Accordingly, a part of the optical path 6 and a part of the optical loop 8 are provided by the optical coupler 10.

The optical loop 8 includes an optical amplifier 12 for compensating for a loss in the optical loop 8 so that laser oscillation occurs in the optical loop 8, an adjuster 14 configured by a delay circuit having a variable delay time τ , and a nonlinear medium (nonlinear optical medium) 16. Particularly in this preferred embodiment, the optical loop 8 further includes an optical bandpass filter 18 having a passband including a

wavelength λ_c of the laser oscillation.

Signal light modulated at a frequency f_s is supplied to the input port 2, and a part of the supplied signal light is introduced through the optical coupler 10 into the optical loop 8. The optical path length L of the optical loop 8 is preliminarily adjusted by the adjuster 14 so that the modulation frequency f_s of the signal light becomes equal to an integral multiple of the reciprocal $\Delta \nu = c/L$ (c : light velocity) of a recirculation period of the optical loop 8. The optical amplifier 12 may be provided by an EDFA (erbium doped fiber amplifier), for example.

Particularly in this preferred embodiment, the nonlinear medium 16 is provided by a third-order nonlinear medium. Without a signal input, a continuous wave at wavelength of λ_c is lased from the optical loop 8. When the signal light is introduced into the nonlinear medium 16, the rasing wave (CW) is amplitude-modulated (AM) or frequency-modulated (FM) in the nonlinear medium 16, and then mode-locked to the frequency of f_s . As a result, clock pulses (optical clock) having a wavelength λ_c and a frequency f_s are generated or regenerated, and the clock pulses are output through the optical coupler 10 from the output port 4. This will now be described

more specifically.

Continuous wave (CW) laser light having a wavelength λ_c is preliminarily oscillated by a ring laser configured by the optical loop 8, and signal light having a wavelength λ_s and a frequency (bit rate or speed) f_s is input into the optical loop 8. At this time, four-wave mixing (FWM) employing this signal light as pump light (excitation light) is generated in the nonlinear medium 16, so that the CW light having the wavelength λ_c is amplitude-modulated by the signal light. The amplitude-modulated CW light includes a component of the fundamental frequency f_s . Accordingly, by setting the optical path length of the optical loop 8 as mentioned above, clock pulses having a frequency f_s are generated.

Thus, clock pulses can be obtained without the need for opto/electric conversion in this preferred embodiment, so that it is possible to provide an all-optical clock regenerator not depending on the bit rate, pulse shape, etc. of signal light.

The nonlinear medium 16 may be provided by a semiconductor optical amplifier (SOA), a single-mode fiber, or a dispersion shifted fiber (DSF). It is effective to use a highly-nonlinear DSF (HNL-DSF) having high nonlinear effects as the DSF.

FIG. 2 shows a second preferred embodiment of the optical device according to the present invention using an SOA 20 as the nonlinear medium 16, and FIG. 3 shows a third preferred embodiment of the optical device according to the present invention using an HNL-DSF 22 as the nonlinear medium 16. In the case of using the SOA 20 as the nonlinear medium 16 as shown in FIG. 2, gain is generated in the nonlinear medium 16. Accordingly, the optical amplifier 12 for maintaining the laser oscillation in the optical loop 8 may be eliminated. More generally, in the case that the linear or nonlinear gain in the nonlinear medium 16 is sufficiently large, the optical amplifier 12 may be eliminated.

In the case that the HNL-DSF 22 is used as the nonlinear medium 16 as shown in FIG. 3, the wavelength λ_s of signal light is preferably set substantially equal to the zero-dispersion wavelength λ_0 of the HNL-DSF 22, so as to most efficiently generate FWM in the nonlinear medium 16. With this setting, optimum phase matching can be attained, and a broadest conversion band and a maximum conversion efficiency can be obtained. The term of "conversion" used herein means conversion from signal light to clock pulses. Further, by managing the zero-dispersion wavelength λ_0 of the HNL-DSF 22 to a constant

value with high accuracy, the conversion band can be broadened. This will now be described more specifically.

The nonlinear coefficient γ of a usual DSF is as small as about $2.6 \text{ W}^{-1}\text{km}^{-1}$. Therefore, to obtain a sufficient conversion efficiency in the case of using such a usual DSF as the nonlinear medium 16 for generating FWM, the fiber is required to have a length of 10 km or more. It is accordingly desired to provide a DSF (HNL-DSF as mentioned above) having a large nonlinear coefficient γ enough to reduce the fiber length. If the length of a DSF used as the nonlinear medium 16 for generating FWM can be reduced, the zero-dispersion wavelength of the DSF can be managed with high accuracy, thereby facilitating exact matching of the wavelength of signal light to the zero-dispersion wavelength of the DSF. As a result, a broad conversion band can be obtained.

In increasing the nonlinear coefficient γ , increasing the nonlinear refractive index n_2 or decreasing a mode field diameter (MFD) corresponding to the effective core area A_{eff} is effective. Increasing the nonlinear refractive index n_2 can be effected by doping the cladding with fluorine or the like or by doping the core with a high concentration of GeO_2 , for example. By doping the core with 25 - 30 mol% of GeO_2 , a large value

of $5 \times 10^{-20} \text{m}^2/\text{W}$ or more is obtained as the nonlinear refractive index n_2 (in comparison, about $3.2 \times 10^{-20} \text{m}^2/\text{W}$ for a normal silica fiber). Decreasing the MFD can be effected by suitably setting a relative index difference Δ or by suitably designing the core shape. For example, by doping the core with 25 - 30 mol% of GeO_2 and setting the relative index difference Δ to 2.5 - 3.0 %, a small value of less than $4 \mu\text{m}$ is obtained as the MFD. As the total effect, a large value of $15 \text{ W}^{-1} \text{km}^{-1}$ or more is obtained as the nonlinear coefficient γ .

Another important factor to be considered is that the DSF providing such a large value as the nonlinear coefficient γ must have a zero-dispersion wavelength substantially coinciding with the wavelength of signal light. Such coincidence between the zero-dispersion wavelength and the wavelength of signal light can be attained by setting the fiber parameters (e.g., relative index difference Δ and MFD) in the following manner. When the relative index difference Δ in a normal optical fiber is increased with the MFD fixed, the dispersion is increased in a normal dispersive region. On the other hand, the larger the core diameter, the smaller the dispersion, while the smaller the core diameter, the larger the dispersion. Accordingly, zero dispersion for

signal light can be obtained by first setting the MFD to a certain value adapted to the band of the signal light and thereafter adjusting the core diameter so that the zero-dispersion wavelength coincides with a predetermined wavelength of the signal light.

A conversion efficiency η_c in an optical fiber having a length L and a loss α can be approximated by the following equation.

$$\eta_c = \exp(-\alpha L)(\gamma P_p L)^2 \quad \dots (1)$$

where P_p is the average pump light power (signal light power). Accordingly, as compared with a normal DSF having a nonlinear coefficient γ of $2.6 \text{ W}^{-1}\text{km}^{-1}$, a fiber having a nonlinear coefficient γ of $15 \text{ W}^{-1}\text{km}^{-1}$ can achieve the same conversion efficiency with a length smaller by $2.6/15 \doteq 1/5.7$. In such a normal DSF, a fiber length of about 10 km is required as mentioned above to obtain a sufficiently large conversion efficiency. To the contrary, in such an HNL-DSF having a large nonlinear coefficient γ as mentioned above, a similar conversion efficiency can be obtained with a smaller length of about 1 - 2 km. In actual, the loss is also reduced by an amount corresponding to the reduction in the fiber length, so that the fiber length can be further reduced to obtain the same conversion efficiency. In such a shorter DSF,

the controllability of the zero-dispersion wavelength is improved and therefore the wavelength of the signal light can be made to exactly coincide with the zero-dispersion wavelength, thus obtaining a broad conversion band. Furthermore, when the fiber length is several kilometers, a polarization plane maintaining ability is ensured, so that the use of such an HNL-DSF is greatly effective in achieving a high conversion efficiency and a broad conversion band and in eliminating polarization dependence.

However, the zero-dispersion wavelength of an actual optical fiber varies along its length because of problems in a manufacturing technique for the optical fiber, with the result that the phase matching condition is deviated from the ideal condition, causing limitation of the conversion band. However, by cutting an optical fiber into a plurality of small sections and then connecting, e.g., splicing the small sections in such an order that the adjacent ones of the small sections have similar zero-dispersion wavelengths (in an order different from the initial order counted from an end of the optical fiber), an optical fiber having a broad conversion band can be obtained with the average of chromatic dispersions over the entire fiber length being

unchanged.

Alternatively, a broad conversion band can be obtained by preparing a plurality of fibers each having a length (e.g., hundreds of meters or less) allowing dispersion management with a high accuracy so required as to obtain a sufficiently broad conversion band, then combining and splicing some of the fibers having required zero-dispersion wavelengths to obtain a fiber having a length required to obtain a required conversion efficiency, and providing a nonlinear medium by use of this fiber.

In the case of broadening the conversion band as mentioned above, it is effective to gather the fiber portions having smaller variations in zero-dispersion wavelength near a pump light (signal light) input end of a nonlinear optical medium, because the power of pump light is higher near the pump light input end. Further, the conversion band can be further broadened by increasing the number of fiber sections as required and/or by alternately arranging the positive and negative signs of dispersion at a portion distant from the pump light input end.

In dividing an optical fiber into a plurality of sections as mentioned above, an index of determining

whether or not the length of each section is sufficiently small may be based on the nonlinear length. It can be considered that phase matching in FWM in a fiber having a length sufficiently smaller than the nonlinear length is dependent on the average dispersion of the fiber. As an example, in FWM using a pump light power of about 30 mW in a fiber having a nonlinear coefficient γ of $2.6 \text{ W}^{-1}\text{km}^{-1}$, the nonlinear length becomes about 12.8 km, so that the above-mentioned index is equal to about 1/10 of this length, i.e., about 1 km. As another example, in FWM using a pump light power of about 30 mW in a fiber having a nonlinear coefficient γ of $15 \text{ W}^{-1}\text{km}^{-1}$, the nonlinear length becomes about 2.2 km, so that the above-mentioned index is equal to about 1/10 of this length, i.e., about 200 m. In any case, by measuring the average zero-dispersion wavelengths of fibers each having a length sufficiently smaller than the nonlinear length, and combining the fibers having substantially the same average zero-dispersion wavelength to provide a nonlinear medium, the conversion efficiency can be increased and the conversion band can be broadened.

The dispersion of the HNL-DSF 22 is preferably set so that no walk-off of two pulses (one of the pulses of the signal light and one of the clock pulses) is

generated. As an example, the zero-dispersion wavelength of the HNL-DSF 22 is set near the middle between the wavelength of the signal light and the wavelength of the clock pulses. Alternatively, the zero-dispersion wavelength is set longer or shorter than the wavelengths of the two pulses. In the case that the zero-dispersion wavelength is set longer than the wavelengths of the two pulses, the dispersion of the HNL-DSF 22 falls in a normal dispersive region, so that modulation instability effects can be suppressed. In the case that the zero-dispersion wavelength is set shorter than the wavelengths of the two pulses, the dispersion of the HNL-DSF 22 falls in an anomalous dispersive region, so that soliton effects can be used. How the zero-dispersion wavelength is set may be determined according to actual system conditions.

In the case of using the HNL-DSF 22 as the nonlinear medium 16 and requiring suppression of stimulated Brillouin scattering (SBS) due to high signal light power, it is desirable to frequency-modulate or phase-modulate the signal light at a frequency sufficiently lower than the bit rate of the signal.

FIG. 4 is a block diagram showing a fourth preferred embodiment of the optical device according to

the present invention. In this preferred embodiment, an optical amplifier 24 is connected between the input port 2 and the optical coupler 10, so as to increase the power of signal light to thereby increase the efficiency of FWM in the nonlinear medium 16. The optical amplifier 24 is provided by an EDFA, for example. Further, an optical bandpass filter 26 is provided between the optical amplifier 24 and the optical coupler 10, so as to remove amplified spontaneous emission (ASE) noise added in the optical amplifier 24. The filter 26 has a passband including the wavelength λ_s of the signal light.

Further, an optical bandpass filter 28 is provided between the optical coupler 10 and the output port 4, so as to extract regenerated clock pulses. The filter 28 has a passband including the wavelength λ_c of the clock pulses. By using the filter 28, the signal light can be removed in the filter 28 to thereby output only the obtained clock pulses from the output port 4.

FIG. 5 is a block diagram showing a preferred embodiment of the system according to the present invention. This system includes an optical fiber transmission line 30 for transmitting signal light, and a plurality of optical repeaters (R) 32 (two being shown) arranged along the optical fiber transmission line 30. A

single optical repeater may be used instead. Signal light is supplied from an optical sender (OS) 34 to the optical fiber transmission line 30, and the signal light transmitted by the optical fiber transmission line 30 is received by an optical receiver (OR) 36.

According to the present invention, each optical repeater 32 can provide so-called 3R functions without the need for opto/electric conversion. The term of "3R" means Reshaping, Retiming, and Regeneration.

FIG. 6 is a block diagram showing a preferred embodiment of each optical repeater 32 shown in FIG. 5. The signal light supplied is split into first and second signal lights at a splitting point 38. The splitting point 38 is provided by an optical coupler, for example. The first signal light is amplified by an optical amplifier 40 with a predetermined gain, and the amplified signal light is then supplied to a waveform shaper 42. On the other hand, the second signal light is supplied to a clock regenerator 44. The clock regenerator 44 regenerates clock pulses by the mode locking of laser oscillation by the signal light according to the present invention. The waveform shaper 42 performs waveform shaping of the signal light by AND gating of the signal light and the clock pulses regenerated by the clock

regenerator 44. Regenerated signal light obtained by the waveform shaping is output from the waveform shaper 42.

More specifically, the waveform shaper 42 has a discriminating function based on optical level such that when the input signal light is composed of pulses having signal intensities higher than a given discrimination point, the pulses are determined to be on-pulses, whereas when the input signal light is composed of pulses having signal intensities lower than the discrimination point, the pulses are determined to be off-pulses. In the case of the on-pulses, the waveform shaper 42 outputs optical pulses, but in the case of the off-pulses, the waveform shaper 42 outputs no optical pulses. By performing the waveform shaping in synchronism with the regenerated clock pulses, signal regeneration based on optical level can be effected with timing being taken.

In the system shown in FIG. 5, the waveform of the signal light is distorted by dispersion and nonlinear effects in the optical fiber transmission line 30, or waveform degradation occurs because of the accumulation of ASE noise in the optical amplifiers during repeated transmission. With the configuration of each optical repeater 32 shown in FIG. 6, the 3R functions can be obtained according to the present invention. Accordingly,

by repeating these functions, long-haul transmission can be effected.

While the optical amplifier 40 is provided between the splitting point 38 and the waveform shaper 42 in the preferred embodiment shown in FIG. 6, the optical amplifier 40 may be provided upstream of the splitting point 38, or inside of the waveform shaper 42, or downstream of the waveform shaper 42. The optical amplifier 40 is provided by an EDFA, for example.

Further, while the optical device according to the present invention is used as the clock regenerator 44 included in each optical repeater 32 in this preferred embodiment, the clock pulses may be regenerated at the output end of the optical fiber transmission line 30 by the optical device according to the present invention. In this case, the optical device according to the present invention is provided in the optical receiver 36, for example.

The waveform shaper 42 may be provided by a device using a saturable absorber, for example. In this case, nonlinear (saturation) effects at a rising region (low-power region) and a peak region (high-power region) of a pulse can be exhibited with respect to the power of input signal light, thereby compressing waveform distortions at

these regions.

FIG. 7 is a block diagram showing a specific embodiment of the optical repeater 32 shown in FIG. 6. A nonlinear optical loop mirror (NOLM) is used as the waveform shaper 42.

More specifically, the waveform shaper 42 includes an optical coupler 50 having optical paths 46 and 48 directionally coupled to each other, a loop optical path 52 for connecting the optical paths 46 and 48, an optical coupler 56 having an optical path 54 directionally coupled to the loop optical path 52. The loop optical path 52 is provided by an HNL-DSF, for example. The optical path 46 is connected to the clock regenerator 44. The optical path 48 serves as an output port of this optical repeater 32. The optical path 54 is connected to the optical amplifier 40.

The clock pulses regenerated by the clock regenerator 44 are supplied as probe pulses to the NOLM, and the signal light amplified by the optical amplifier 40 is supplied as control pulses to the NOLM. The power P_s of the input signal light is adjusted so that a difference Φ in phase shift due to cross-phase modulation (XPM) between clock pulses propagating clockwise in the loop optical path 52 and clock pulses propagating

counterclockwise in the loop optical path 52 after split at the optical coupler 50 becomes about π . At this time, switching of the clock pulses occurs and the regenerated signal light subjected to waveform shaping is generated with the same wavelength as that of the clock pulses.

The dispersion of the HNL-DSF used as the loop optical path 52 is preferably set so that no walk-off of two pulses (one of the pulses of the signal light and one of the clock pulses) is generated. As an example, the zero-dispersion wavelength of the HNL-DSF is set near the middle between the wavelength of the signal light and the wavelength of the clock pulses. Alternatively, the zero-dispersion wavelength is set longer or shorter than the wavelengths of the two pulses. In the case that the zero-dispersion wavelength is set longer than the wavelengths of the two pulses, the dispersion of the HNL-DSF falls in a normal dispersive region, so that modulation instability effects can be suppressed. In the case that the zero-dispersion wavelength is set shorter than the wavelengths of the two pulses, the dispersion of the HNL-DSF falls in an anomalous dispersive region, so that soliton effects can be used. How the zero-dispersion wavelength is set may be determined according to actual system conditions.

Further, an optical filter and an optical isolator may be provided upstream or downstream of the configuration shown in FIG. 7 or inside of the configuration shown in FIG. 7.

While the NOLM is used as the waveform shaper in the above preferred embodiment for illustration, an interferometer configuration in accordance with a similar principle may be used instead.

According to the present invention as described above, it is possible to provide a method, device, and system for regeneration and application of an optical clock not depending on the bit rate, pulse shape, etc. of signal light without the need for opto/electric conversion. As a result, various performance limits in the existing linear optical communication system can be broken down.

The present invention is not limited to the details of the above described preferred embodiments. The scope of the invention is defined by the appended claims and all changes and modifications as fall within the equivalence of the scope of the claims are therefore to be embraced by the invention.

WHAT IS CLAIMED IS:

1. An optical device comprising:

an optical path provided between an input port to which signal light modulated at a frequency f_s is supplied and an output port; and

an optical loop optically coupled to said optical path;

said optical loop comprising:

an optical amplifier for compensating for a loss in said optical loop so that laser oscillation occurs in said optical loop;

an adjuster for adjusting an optical path length of said optical loop so that said frequency f_s becomes equal to an integral multiple of the reciprocal of a recirculation period of said optical loop; and

a nonlinear optical medium for mode-locking said laser oscillation according to said signal light.

2. An optical device according to claim 1, wherein said optical loop further comprises an optical bandpass filter having a passband including the wavelength of said laser oscillation.

3. An optical device according to claim 1, further comprising an optical coupler for optically coupling said optical path and said optical loop, said optical coupler

providing a part of said optical path and a part of said optical loop.

4. An optical device according to claim 1, wherein:
said nonlinear optical medium comprises a third-order nonlinear optical medium; and
amplitude modulation is performed in said nonlinear optical medium by four-wave mixing using said signal light as pump light.

5. An optical device according to claim 1, wherein said nonlinear optical medium comprises a semiconductor optical amplifier.

6. An optical device according to claim 1, wherein said nonlinear optical medium comprises a single-mode fiber.

7. An optical device according to claim 1, wherein said nonlinear optical medium comprises a highly-nonlinear dispersion shifted fiber.

8. An optical device according to claim 6 or 7, wherein said nonlinear optical medium has a zero-dispersion wavelength substantially equal to the wavelength of said signal light.

9. An optical device according to claim 1, further comprising an input optical amplifier optically connected to said input port for amplifying said signal light.

10. An optical device according to claim 9, further comprising an optical bandpass filter optically connected between said input port and said input optical amplifier and having a passband including a wavelength of said signal light.

11. An optical device according to claim 1, further comprising an optical bandpass filter optically connected to said output port and having a passband including a wavelength of light obtained by said laser oscillation.

12. An optical device according to claim 1, further comprising a waveform shaper optically connected to said output port for performing waveform shaping of said signal light according to an optical clock output from said output port.

13. An optical device according to claim 12, wherein said waveform shaper comprises a nonlinear optical loop mirror.

14. A system comprising:

an optical fiber transmission line for transmitting signal light modulated at a frequency f_s ; and

an optical device connected to an output end of said optical fiber transmission line;

said optical device comprising:

an optical path provided between an input port to

which said signal light is supplied and an output port;
and

an optical loop optically coupled to said optical
path;

said optical loop comprising:

an optical amplifier for compensating for a loss in
said optical loop so that laser oscillation occurs in
said optical loop;

an adjuster for adjusting the optical path length
of said optical loop so that said frequency f_s becomes
equal to an integral multiple of the reciprocal of a
recirculation period of said optical loop; and

a nonlinear optical medium for mode-locking said
laser oscillation according to said signal light.

15. A system comprising:

an optical fiber transmission line for transmitting
signal light; and

at least one optical repeater arranged along said
optical fiber transmission line;

each of said at least one optical repeater
comprising:

an optical clock regenerator for regenerating an
optical clock by mode locking of laser oscillation
according to said signal light; and

a waveform shaper for performing waveform shaping of said signal light according to said optical clock regenerated by said optical clock regenerator.

16. A system according to claim 15, wherein said waveform shaper comprises a nonlinear optical loop mirror.

17. A method comprising the steps of:

(a) generating laser oscillation in an optical loop including a nonlinear optical medium;

(b) introducing signal light modulated at a frequency f_s into said optical loop;

(c) adjusting the optical path length of said optical loop so that said frequency f_s becomes equal to an integral multiple of the reciprocal of a recirculation period of said optical loop; and

(d) regenerating an optical clock by mode-locking said laser oscillation according to said signal light.

ABSTRACT OF THE DISCLOSURE

The present invention relates to an optical device for regenerating an optical clock. The optical device includes an optical path provided between an input port to which signal light modulated at a frequency f_s is supplied and an output port, and an optical loop optically coupled to the optical path. The optical loop includes an optical amplifier for compensating for a loss in the optical loop so that laser oscillation occurs in the optical loop, an adjuster for adjusting the optical path length of the optical loop so that the frequency f_s becomes equal to an integral multiple of the reciprocal of a recirculation period of the optical loop, and a nonlinear optical medium for mode-locking the laser oscillation according to the signal light. For example, in the nonlinear optical medium, four-wave mixing using the signal light as pump light is generated by third-order nonlinear effects to perform amplitude modulation and regenerate an optical clock at the wavelength of the laser oscillation.

FIG. 1




FIG. 2




FIG. 3




FIG. 4





FIG. 5



Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

Declaration and Power of Attorney For Patent Application

特許出願宣言書及び委任状

Japanese Language Declaration

日本語宣言書

下記の氏名の発明者として、私は以下の通り宣言します。

As a below named inventor, I hereby declare that:

私の住所、私書箱、国籍は下記の私の氏名の後に記載された通りです。

My residence, post office address and citizenship are as stated next to my name.

下記の名称の発明に関して請求範囲に記載され、特許出願している発明内容について、私が最初かつ唯一の発明者（下記の氏名が一つの場合）もしくは最初かつ共同発明者であると（下記の名称が複数の場合）信じています。

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled

METHOD, DEVICE, AND SYSTEM FOR
REGENERATION AND APPLICATION OF
OPTICAL CLOCK

上記発明の明細書（下記の欄でX印がついていない場合は、本表に添付）は、

the specification of which is attached hereto unless the following box is checked:

☐ 月 日に提出され、米国出願番号または特許協定条約国際出願番号を _____ とし、
（該当する場合） _____ に訂正されました。☐ was filed on _____
as United States Application Number or
PCT International Application Number
_____ and was amended on
_____ (if applicable).

私は、特許請求範囲を含む上記訂正後の明細書を検討し、内容を理解していることをここに表明します。

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

私は、連邦規則法典第37編第1条56項に定義されるとおり、特許資格の有無について重要な情報を開示する義務があることを認めます。

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, Section 1.56.

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

Japanese Language Declaration

(日本語宣言書)

私は、米国法典第35編119条(a)-(d)項又は365条(b)項に基づき下記の、米国以外の国の少なくとも一ヶ国を指定している特許協力条約365(a)項に基づく国際出願、又は外国での特許出願もしくは発明者証の出願についての外国優先権をここに主張するとともに、優先権を主張している、本出願の前に出願された特許または発明者証の外国出願を以下に、枠内をマークすることで、示しています。

Prior Foreign Application(s)

外国での先行出願

11-133423
(Number)
(番号)

Japan
(Country)
(国名)

(Number)
(番号)

(Country)
(国名)

I hereby claim foreign priority under Title 35, United States Code, Section 119 (a)-(d) or 365(b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT International application which designated at least one country other than the United States, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or PCT International application having a filing date before that of the application on which priority is claimed.

Priority Not Claimed

優先権主張なし

14 May 1999

(Day/Month/Year Filed)
(出願年月日)

☐

(Day/Month/Year Filed)
(出願年月日)

☐

私は、第35編米国法典119条(e)項に基づいて下記の米国特許出願規定に記載された権利をここに主張いたします。

(Application No.)
(出願番号)

(Filing Date)
(出願日)

(Application No.)
(出願番号)

(Filing Date)
(出願日)

私は、下記の米国法典第35編120条に基づいて下記の米国特許出願に記載された権利、又は米国を指定している特許協力条約365条(c)に基づき権利をここに主張します。また、本出願の各請求範囲の内容が米国法典第35編112条第1項又は特許協力条約で規定された方法で先行する米国特許出願に開示されていない限り、その先行米国出願書提出日以降で本出願書の日本国内または特許協力条約国際提出日までの期間中に入手された、連邦規則法典第37編1条56項で定義された特許資格の有無に関する重要な情報について開示義務があることを認識しています。

(Application No.)
(出願番号)

(Filing Date)
(出願日)

(Application No.)
(出願番号)

(Filing Date)
(出願日)

I hereby claim the benefit under Title 35, United States Code, Section 120 of any United States application(s), or 365(c) of any PCT International application designating the United States, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application in the manner provided by the first paragraph of Title 35, United States Code Section 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, Section 1.56 which became available between the filing date of the prior application and the national or PCT International filing date of application.

(Status: Patented, Pending, Abandoned)
(現況: 特許許可済、係属中、放棄済)

(Status: Patented, Pending, Abandoned)
(現況: 特許許可済、係属中、放棄済)

私は、私自身の知識に基づいて本宣言書中で私が行なう表明が真実であり、かつ私の入手した情報と私の信じることに基づき表明が全て真実であると信じていること、さらに故意になされた虚偽の表明及びそれと同等の行為は米国法典第18編第1001条に基づき、罰金または拘禁、もしくはその両方により処罰されること、そしてそのような故意による虚偽の表明を行えば、出願した、又は発明者証に提出された特許の有効性が失われることを認識し、よってここに上記のごとく宣誓を致します。

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

Japanese Language Declaration

(日本語宣言書)

委任状: 私は下記の発明者として、本出願に関する一切の
手続を米特許審判局に対して遂行する弁理上または代理人
として、下記の者を指名いたします。(弁理上、または代理
人氏名及び登録番号を明記のこと)

POWER OF ATTORNEY: As a named inventor, I hereby appoint
the following attorney(s) and/or agent(s) to prosecute this
application and transact all business in the Patent and Trademark
Office connected therewith (list name and registration number)

James D. Halsey, Jr., 22,729; Harry John Staas, 22,010; David M. Pitcher, 25,908; John C. Garvey, 28,607; J. Randall Beckers, 30,358;
William F. Herbert, 31,024; Richard A. Gollhofer, 31,106; Mark J. Henry, 36,162; Gene M. Garner II, 34,172; Michael D. Stein, 37,240; Paul
I. Kravetz, 35,230; Gerald P. Joyce, III, 37,648; Todd E. Marlette, 35,269; Harlan B. Williams, Jr., 34,756; George N. Stevens, 36,938;
Michael C. Soldner, P-41,455 and William M. Schertler, 35,348 (agent)

書類送付先

Send Correspondence to:

STAAS & HALSEY
700 Eleventh Street, N.W.
Suite 500
Washington, D.C. 20001

直接電話連絡先 (名前及び電話番号)

Direct Telephone Calls to: (name and telephone number)

STAAS & HALSEY
(202) 434-1500

唯一または第一発明者名	Full name of sole or first inventor Shigeki Watanabe		
発明者の署名	日付	Inventor's signature Shigeki Watanabe	Date April 18, 2000
住所	Residence Kawasaki-shi, Japan		
国籍	Citizenship Japanese		
私書箱	Post Office Address C/O FUJITSU LIMITED, 1-1, Kamikodanaka		
	4-chome, Nakahara-ku, Kawasaki-shi, Kanagawa 211-8588 Japan		
第二共同発明者	Full name of second joint inventor, if any		
第二共同発明者	日付	Second inventor's signature	Date
住所	Residence		
国籍	Citizenship		
私書箱	Post Office Address		

(第三以降の共同発明者についても同様に記載し、署名をす
ること)

(Supply similar information and signature for third and subsequent
joint inventors.)